

LamaPLC: AHT20 / BMP280 Modul

This compact module integrates an AHT20 sensor for air temperature and humidity with a BMP280 sensor for air pressure, offering a complete overview of environmental conditions. Both sensors are popular for their accuracy and small size. Communication is straightforward through the **I²C** interface, compatible with various microcontrollers, with an operating voltage range of 2-5V.



Technical Details

- Operating voltage: DC 2..5V
- Sensors: AHT20, BMP280
- Dimensions: 16 x 16.5 x 3 mm
- Weight: 4 g
- *I²C Addresses*

 - BMP280: 0x77
 - AHT20: 0x38

- *Air pressure*

 - Measurement range: 300 to 1100 hPa
 - Resolution: 0.18 Pa
 - Accuracy: ±1 Pa

- *Humidity*

 - Resolution: 0.024 %RH
 - Tolerance: ±2 %RH
 - Reproducibility: ±0.1 %RH
 - Response time: 8 seconds
 - Measurement range: 0-100 %RH
 - Long-term drift: □0.5 %RH/year

- *Temperature*

 - Resolution: 0.01°C
 - Tolerance: ±0.3°C
 - Reproducibility: ±0.1°C
 - Response time: minimum 5 seconds, maximum 30 seconds
 - Measurement range: -40°C to 85°C
 - Long-term drift: □0.04°C/year



If you'd like to support the development of the site with the price of a coffee — or a few — [please do so here](#).

Here's a handy tip: you can quickly save this page as a PDF by clicking "export to PDF" in the menu on the right side of the screen.

2026/02/14 23:38

Arduino wiring

- SCL: A5
- GND: GND
- SDA: A4
- Vdd: 5V

Arduino code

For some reason, the Adafruit BMP280 library doesn't work reliably. It eventually freezes so severely that it only functions when the Arduino is powered off. I tried different parameter settings, but it didn't make a difference. It seems that the [BMx280MI](#) library written by Gregor Christandl works better.

```
// lamaPLC AHT20+BMP280 module test
// 2025.10.08. free code

#include <Arduino.h>
#include <Wire.h>
#include <Adafruit_AHTX0.h>
#include <BMx280I2C.h>

#define I2C_ADDRESS 0x77

Adafruit_AHTX0 aht;

BMx280I2C bmx280(I2C_ADDRESS);

void(* resetFunc) (void) = 0; //declare reset function @ address 0

void setup() {
  Serial.begin(9600);
  Wire.begin();
  Serial.println("AHT20+BMP280 module test");

  if (!aht.begin()) {
    Serial.println("Could not find a valid AHT20 sensor, check wiring!");
    while (1);
  }

  if (!bmx280.begin()) {
    Serial.println("Could not find a valid BMP280 sensor, check wiring!");
    while (1);
  }

  bmx280.resetToDefaults();

  //set an oversampling setting for pressure and temperature measurements.
  bmx280.writeOversamplingPressure(BMx280MI::OSRS_P_x16);
```

```
    bmx280.writeOversamplingTemperature(BMx280MI::0SRS_T_x16);

    Serial.println("AHT20 / BMP280 module ok");
}

void loop() {
    Serial.println("check -----");

    //start AHT20 measurement
    sensors_event_t humidity, temp;
    aht.getEvent(&humidity, &temp);
    Serial.print("AHT 20 Temperature: "); Serial.print(temp.temperature);
    Serial.println(" degrees C");
    Serial.print("AHT 20 Humidity: ");
    Serial.print(humidity.relative_humidity); Serial.println("% rH");

    //start BMP280 measurement
    if (!bmx280.measure())
    {
        Serial.println("could not start measurement, is a measurement
already running?");
        return;
    }

    //wait for the measurement to finish
    do
    {
        delay(100);
    } while (!bmx280.hasValue());

    Serial.print("BMP280 Pressure: "); Serial.print(bmx280.getPressure());
    Serial.println(" Pa");
    Serial.print("BMP280 Pressure (64 bit): ");
    Serial.print(bmx280.getPressure64()); Serial.println(" Pa");
    Serial.print("BMP280 Temperature: ");
    Serial.print(bmx280.getTemperature()); Serial.println(" degrees C");

    Serial.println();
    delay(5000);
}
```

code in github: <https://github.com/lamaPLC/AHT20-BMP280-Modul-Arduino-code>

Output on the serial monitor:

```
check -----
AHT 20 Temperature: 22.12 degrees C
AHT 20 Humidity: 62.55% rH
BMP280 Pressure: 99128.00 hPa
```

BMP280 Pressure (64 bit): 99125.84 hPa
 BMP280 Temperature: 23.17 degrees C

Example codes

[Arduino - OLED SH1106 with AHT20/BMP280 Sensor](#)

I²C topics on lamaPLC

Page	Date	Tags
• lamaPLC Communication: 1-Wire	2026/04/23 21:51	1-wire , communication , bus , microlan , i2c , uart , usart , ds18b20
• lamaPLC Communication: I²C	2025/09/23 21:25	i2c , i c , smbus , philips , bus , communication , arduino
• lamaPLC project: Sension SCD CO² measurement module	2026/04/15 19:34	scd30 , scd40 , scd41 , iaq , ndir , sensor , i2c , arduino code
• LamaPLC: AHT10 Modul	2026/03/22 03:14	communication , i2c , temperature , humidity , sensor , aht , aht 10 , modul
• LamaPLC: AHT20 / BMP280 Modul	2026/04/23 21:52	bmp280 , aht20 , adafruit , temperature , humidity , pressure , sensor , arduino , code , i2c
• LamaPLC: APDS - Avago ALS and proximity detection sensors with I²C communication	2026/04/23 21:52	avago , apds-9900 , apds-9930 , apds-9960 , als , proximity , detection , gesture recognition , gesture , i2c , communication , sensor , arduino , code
• lamaPLC: AS5600 Magnetic Induction Angle Measurement Sensor Module	2026/03/28 23:50	communication , i2c , as5600 , as-5600 , magnetic , induction , angle , sensor
• lamaPLC: Bi-Directional Logic Level Converter 3.3V ↔ 5V	2026/04/12 00:34	bi-directional , logic level converter , i2c , uart , spi
• LamaPLC: BMP/BME Bosch Temperature/Humidity/Pressure sensors with I²C communication	2026/04/23 21:52	bme280 , bme680 , bmp180 , bmp280 , hw-611 , hw611 , bosch , temperature , humidity , pressure , sensor , arduino , i2c , communication , cjmcu
• LamaPLC: CJMCU-219/INA-219 breakout board/IC with I²C communication	2026/04/23 21:52	cjmcu-219 , ina-219 , ina219 , breakout board , i2c , communication , sensor , voltage , current , arduino , code , cjmcu
• LamaPLC: CJMCU-3216 / AP-3216 integrated digital ambient light and proximity sensor module/IC with I²C communication	2026/04/23 21:52	cjmcu-3216 , cjmcu , ap-3216 , ap3216 , ambient light , proximity , sensor , arduino , code , i2c , communication
• lamaPLC: CJMCU-811 CCS811 Gas Sensor (VOCs TVOC CO₂)	2026/03/22 00:08	cjmcu-811 , ccs811 , gas , sensor , vocs , tvoc , eco2 , co2 , arduino , air quality , metal oxide , mox , i2c
• LamaPLC: D6T Omron Non-Contact Thermal Sensors with I²C communication	2026/04/23 21:52	d6t , d6t-32l , d6t-44l , d6t-8l , d6t-1a , omron , non-contact , thermal , sensor , i2c , arduino , code

• LamaPLC: DPS Infineon Temperature/Pressure sensors with I2C communication	2026/04/23 21:52	dps310, infineon, temperature, pressure, sensor, arduino, i2c, communication, code
• lamaPLC: Energy, power, current, and voltage	2025/05/31 23:32	i2c, i c, communication, arduino, energy, power, current, sensor, ina226
• LamaPLC: ENS ScioSense Multi-gas sensors with I ² C communication	2026/04/23 21:52	ens160, sciosense, gas-quality, i2c, communication, sensor, arduino, code, eco2, tvoc, aqi, indoor air quality, iaq, co2, voc
• lamaPLC: ESP32 / ESP8266	2025/11/22 00:07	esp8266, esp32, esp32-c2, esp32-c3, esp32-c5, esp32-c6, esp32-c61, esp32-h2, esp32-s2, esp32-s3, esp32-p4, espressif systems, communication, ethernet, ip, wi-fi, thread, zigbee, matter, homekit, bluetooth, mqtt, adc, spi, uart, i2c, i2s, rmt, pwm, usb, usb otg, twai
• LamaPLC: Gas sensors	2023/07/01 17:29	gas, sensor, i2c, onewire, communication, mq-3, mq-4, mq-5, mq-6, mq-7, mq-8, mq-9, mq-135, gm-102b, gm-302b, gm-502b, gm-702b, alcohol, ch4, natural gas, smoke, lng, co, co2, lpg, h2, iso-butane, nox, nh3, benzene, town gas, formaldehyde, propane, humidity, temperature, voc, grv gas sens v2
• lamaPLC: GY-511 6DOF sensor module	2026/03/22 01:44	stmicroelectronics, lsm303dlhc, i2c, lsm303, sensor, gy-511, 6dof, pololu, module, arduino
• LamaPLC: GY-9250 MPU-9250/6500 9-axis Attitude Sensor Board	2026/04/23 21:52	ak8963, gy-9250, mpu-9250, 9-axis, motion detection, magnetometer, communication, i c, i2c, spi
• LamaPLC: HDC Texas Instruments Temperature/humidity sensors with I ² C communication	2026/04/23 21:52	sht21, htu21, si7021, gy-21, gy-213v, hdc1080, gy-213v-hdc1080, cjmcu, cjmcu-1080, texas instruments, temperature, humidity, sensor, i2c, communication, arduino, code
• lamaPLC: HT16K33 display controller	2026/04/23 21:51	i2c, 7-segment display, display, ht16k33, arduino
• LamaPLC: HTU TE Connectivity temperature/humidity sensors with I ² C communication	2026/04/23 21:52	htu, htu31d, htu21d, htu20d, sht20, htu20, sht21, htu21, si7021, gy-21, gy-213v, hdc1080, si702, gy-20, sht31, htu31, si7031, gy-31, te connectivity, temperature, humidity, i2c, communication, sensor, arduino, code
• lamaPLC: INA modules with Arduino libraries	2026/04/11 19:54	i2c, i c, communication, arduino, energy, power, current, monitor, sensor, ina219, gy-219, ina226, gy-216, ina228, gy-228, ina237, ina238, ina260, ina3221, ina
• lamaPLC: INA226 - current/voltage/power monitor with I ² C communication	2026/04/23 21:52	i2c, i c, communication, arduino, energy, power, current, monitor, sensor, ina226, ina219, ina

• lamaPLC: LCD 1602/2004 with I²C communication	2026/02/14 18:27	communication , i2c , display , lcd , 1602 , 2004 , hd44780 , pcf8574 , pcf8574t , pcf8574at , arduino
• LamaPLC: MAX30100/MAX30102 Heart Rate Click Sensor Module	2026/04/23 21:52	max30102 , max30100 , heart rate click , sensor , communication , i2c , arduino , code
• lamaPLC: MCP23017 / MCP23S17 16-Bit I/O Expander with Serial Interface I²C / SPI	2026/04/23 21:52	communication , i2c , mcp23017 , mcp23s17 , spi , i o expander , serial , cjmcu-2317 , cjmcu
• LamaPLC: Pixart PAJ7620U2 Gesture recognition sensors/module with I²C communication	2026/04/23 21:52	paj7620u2 , gy-paj7620 , pixart , gesture recognition , i2c , communication , sensor , arduino , code
• LamaPLC: SC16IS750 / SC16IS752: One or two serial (UART) ports from microcontroller via I²C or SPI communication	2026/04/23 21:52	cjmcu-750 , cjmcu-752 , cjmcu , nxp , sc16is750 , sc16is752 , uart , serial , i2c , spi , modul , converter , arduino , code
• LamaPLC: SGP Sensirion TVOC/VOC sensors with I²C communication	2026/04/15 19:41	sgp30 , sgp40 , sgp41 , sensirion , gas-sensor , i2c , communication , sensor , arduino , code , eco2 , voc , tvoc , indoor air quality , iaq , nox , hydrogen
• LamaPLC: SHT Sensirion Temperature/humidity sensor with I²C communication	2026/04/23 21:52	sht20 , sht21 , sht25 , sht30 , sht31 , sht35 , sht40 , gy21 , temperature , humidity , i2c , communication , sensor , arduino , code
• lamaPLC: Signal level converters	2026/02/14 23:47	pca9306 , i2c , voltage , level , converter
• lamaPLC: TCA9548A (HW617); Low-Voltage 8-Channel I²C Switch Module	2026/02/14 23:51	tca9548a , hw617 , i2c , switch , communication , expansion board , arduino
• lamaPLC: TM1637 7-segment display	2026/02/14 18:26	i2c , 7-segment display , display , tm1637 , arduino
• LamaPLC: TOFnnnC STMicroelectronics Time-of-Flight (ToF) sensors with I²C communication	2026/04/23 21:52	tof050c , vl6180 , tof200c , vl53l0x , tof400c , vl53l1x , stmicroelectronics , time-of-flight , tof , i2c , communication , sensor , arduino , code
• LamaPLC: VL53Lnn STMicroelectronics time-of-flight (ToF) laser-ranging sensors with I²C communication	2026/04/23 21:52	vl53l0x , vl53l1x , vl53l0 1xv2 , gy-530 , time-of-flight , tof , laser-ranging , i2c , communication , sensor , arduino , code
• LamaPLC: VL6180X STMicroelectronics Time-of-Flight (ToF) sensor with I²C communication	2026/04/23 21:52	vl6180x , stmicroelectronics , time-of-flight , tof , i2c , communication , sensor , arduino , code
• Magnetic angle sensors	2026/03/05 21:19	magnetic angle sensor , magnetic flux , sensor , spi , i2c , pwm , communication , modul , as5047p , as5600 , mt6701 , mt6816 , mt6835 , tle5012b , amr , gmr , tmr , anisotropic magnetoresistive
• SSH1106/SSD1306 OLED Display with I²C communication	2026/02/14 18:27	i2c , oled , display , ssd1306 , sh1106 , ssh1106 , arduino , cmos

[BMP280](#), [AHT20](#), [Adafruit](#), [temperature](#), [humidity](#), [pressure](#), [sensor](#), [arduino](#), [code](#), [i2c](#)

This page has been accessed for: Today: 3, Until now: 21

From:

<https://www.lamaplc.de/> - **lamaPLC**

Permanent link:

https://www.lamaplc.de/doku.php?id=sensor:aht20_bmp280

Last update: **2026/04/21 20:47**

