







# LamaPLC: DHT Temperature /Humidity sensors with 1-wire / I<sup>2</sup>C communication

The DHT is a popular, low-cost digital sensor that measures both temperature and humidity. DHT22 offers higher accuracy than its predecessor, the DHT11. It is suitable for a wide range of applications, including weather stations and smart home systems.

Type of measurement	Model	Power voltage	Measurement, range, accuracy	Communication	Note
 Temperature Humidity	<b>DHT11</b> 	<b>3.3 / 5 V</b> (3.3 .. 5.5V)	Temperature measurement range: 0 .. +50 °C Temperature measurement accuracy: ±2°C Humidity measurement range: 20..90% RH Humidity measurement accuracy: ±5%	1-Wire	8 bit resolution, response time 10 sec
 Temperature Humidity	<b>DHT20</b> 	<b>3.3 / 5 V</b> (2.2 .. 5.5V)	Temperature measurement range: -40 .. +80 °C Temperature measurement accuracy: ±0.5°C (-40..80) Humidity measurement range: 0..100% RH Humidity measurement accuracy: ±3%	I <sup>2</sup> C default addr.: <b>0x38</b>	-
 Temperature Humidity	<b>DHT22 AM2302</b> 	<b>3.3 / 5 V</b> (2.2 .. 5.5V)	Temperature measurement range: -40 .. +80 °C Temperature measurement accuracy: ±0.5°C (-40..80) Humidity measurement range: 0..100% RH Humidity measurement accuracy: ±2%	single-bus	-

## Operation and Usage

The DHTs use a single bus for communication, which requires careful timing; this is typically handled by libraries in microcontroller environments. A 4.7kΩ to 10kΩ pull-up resistor is needed between the data line and VCC for proper communication.

The sensors are available in two main forms: a 4-pin bare sensor and a 3-pin module with the pull-up resistor integrated.

The BME/BMP sensors can be integrated with the [Tasmota](#) system. For more details, see here:

- DHT11 sensors: <https://tasmota.github.io/docs/DHT11/>



If you'd like to support the development of the site with the price of a coffee — or a few — [please do so here](#).

Here's a handy tip: you can quickly save this page as a PDF by clicking "export to PDF" in the menu on the right side of the screen.

2026/02/14 23:38

## Arduino & DHT22

To read a DHT22 sensor with an Arduino, you typically use the **Adafruit DHT Sensor Library** along with the Adafruit Unified Sensor Library.

### Wiring Details

The wiring depends on whether you have a bare sensor or a module:

- **VCC:** 3.3V to 5V.
- **GND:** Ground.
- **Data (DQ):** Digital pin (e.g., Pin 2).
- **Pull-up Resistor:** Bare 4-pin sensors require a 4.7kΩ to 10kΩ pull-up resistor from VCC to Data. Modules with 3 pins usually have this resistor built-in.

### Arduino Example Code

This sketch reads temperature (in Celsius) and humidity every 2 seconds.

```
#include "DHT.h"

#define DHTPIN 2      // Digital pin connected to the DHT sensor
#define DHTTYPE DHT22 // DHT 22 (AM2302), AM2321

// Initialize DHT sensor.
DHT dht(DHTPIN, DHTTYPE);

void setup() {
  Serial.begin(9600);
  Serial.println(F("DHT22 test!"));
  dht.begin();
}

void loop() {
  delay(2000); // Wait 2 seconds between measurements

  // Read humidity and temperature
  float h = dht.readHumidity();
```

```

float t = dht.readTemperature();
float f = dht.readTemperature(true); // Temperature in Fahrenheit

// Check for read failures
if (isnan(h) || isnan(t) || isnan(f)) {
  Serial.println(F("Failed to read from DHT sensor!"));
  return;
}

// Print results
Serial.print(F("Humidity: "));
Serial.print(h);
Serial.print(F("% Temperature: "));
Serial.print(t);
Serial.print(F("°C "));
Serial.print(f);
Serial.println(F("°F"));
}

```

## 1-wire, I2C topics on lamaPLC

Page	Date	Tags
• <a href="#">lamaPLC Communication: 1-Wire</a>	2026/04/23 21:51	1-wire, communication, bus, microlan, i2c, uart, usart, ds18b20
• <a href="#">lamaPLC Communication: IEC 61850 basic</a>	2026/04/23 21:51	1-wire, communication, bus, xml, iec 61850, iec, ethernet, scl, goose, ied
• <a href="#">lamaPLC Communication: I<sup>2</sup>C</a>	2025/09/23 21:25	i2c, i c, smbus, philips, bus, communication, arduino
• <a href="#">LamaPLC: AHT10 Modul</a>	2026/03/22 03:14	communication, i2c, temperature, humidity, sensor, aht, aht 10, modul
• <a href="#">LamaPLC: AHT20 / BMP280 Modul</a>	2026/04/23 21:52	bmp280, aht20, adafruit, temperature, humidity, pressure, sensor, arduino, code, i2c
• <a href="#">LamaPLC: APDS - Avago ALS and proximity detection sensors with I<sup>2</sup>C communication</a>	2026/04/23 21:52	avago, apds-9900, apds-9930, apds-9960, als, proximity, detection, gesture recognition, gesture, i2c, communication, sensor, arduino, code
• <a href="#">lamaPLC: AS5600 Magnetic Induction Angle Measurement Sensor Module</a>	2026/03/28 23:50	communication, i2c, as5600, as-5600, magnetic, induction, angle, sensor
• <a href="#">lamaPLC: Bi-Directional Logic Level Converter 3.3V ↔ 5V</a>	2026/04/12 00:34	bi-directional, logic level converter, i2c, uart, spi
• <a href="#">LamaPLC: BMP/BME Bosch Temperature/Humidity/Pressure sensors with I<sup>2</sup>C communication</a>	2026/04/23 21:52	bme280, bme680, bmp180, bmp280, hw-611, hw611, bosch, temperature, humidity, pressure, sensor, arduino, i2c, communication, cjmcu
• <a href="#">LamaPLC: CJMCU-219/INA-219 breakout board/IC with I<sup>2</sup>C communication</a>	2026/04/23 21:52	cjmcu-219, ina-219, ina219, breakout board, i2c, communication, sensor, voltage, current, arduino, code, cjmcu

<ul style="list-style-type: none"> <li>• <a href="#">LamaPLC: CJMCU-3216 / AP-3216 integrated digital ambient light and proximity sensor module/IC with I<sup>2</sup>C communication</a></li> </ul>	2026/04/23 21:52	<a href="#">cjmcu-3216</a> , <a href="#">cjmcu</a> , <a href="#">ap-3216</a> , <a href="#">ap3216</a> , <a href="#">ambient light</a> , <a href="#">proximity</a> , <a href="#">sensor</a> , <a href="#">arduino</a> , <a href="#">code</a> , <a href="#">i2c</a> , <a href="#">communication</a>
<ul style="list-style-type: none"> <li>• <a href="#">lamaPLC: CJMCU-811 CCS811 Gas Sensor (VOCs TVOC CO2)</a></li> </ul>	2026/03/22 00:08	<a href="#">cjmcu-811</a> , <a href="#">ccs811</a> , <a href="#">gas</a> , <a href="#">sensor</a> , <a href="#">vocs</a> , <a href="#">tvoc</a> , <a href="#">eco2</a> , <a href="#">co2</a> , <a href="#">arduino</a> , <a href="#">air quality</a> , <a href="#">metal oxide</a> , <a href="#">mox</a> , <a href="#">i2c</a>
<ul style="list-style-type: none"> <li>• <a href="#">LamaPLC: D6T Omron Non-Contact Thermal Sensors with I<sup>2</sup>C communication</a></li> </ul>	2026/04/23 21:52	<a href="#">d6t</a> , <a href="#">d6t-32l</a> , <a href="#">d6t-44l</a> , <a href="#">d6t-8l</a> , <a href="#">d6t-1a</a> , <a href="#">omron</a> , <a href="#">non-contact</a> , <a href="#">thermal</a> , <a href="#">sensor</a> , <a href="#">i2c</a> , <a href="#">arduino</a> , <a href="#">code</a>
<ul style="list-style-type: none"> <li>• <a href="#">LamaPLC: DHT Temperature /Humidity sensors with 1-wire / I<sup>2</sup>C communication</a></li> </ul>	2026/04/23 21:52	<a href="#">dht11</a> , <a href="#">dht20</a> , <a href="#">dht22</a> , <a href="#">temperature</a> , <a href="#">humidity</a> , <a href="#">pressure</a> , <a href="#">sensor</a> , <a href="#">1-wire</a> , <a href="#">arduino</a> , <a href="#">code</a>
<ul style="list-style-type: none"> <li>• <a href="#">LamaPLC: DPS Infineon Temperature/Pressure sensors with I2C communication</a></li> </ul>	2026/04/23 21:52	<a href="#">dps310</a> , <a href="#">infineon</a> , <a href="#">temperature</a> , <a href="#">pressure</a> , <a href="#">sensor</a> , <a href="#">arduino</a> , <a href="#">i2c</a> , <a href="#">communication</a> , <a href="#">code</a>
<ul style="list-style-type: none"> <li>• <a href="#">lamaPLC: DS18B20 1-Wire Digital Thermometer</a></li> </ul>	2026/04/23 21:52	<a href="#">ds18b20</a> , <a href="#">sensor</a> , <a href="#">1-wire</a> , <a href="#">communication</a> , <a href="#">arduino</a> , <a href="#">thermometer</a> , <a href="#">parasitic mode</a>
<ul style="list-style-type: none"> <li>• <a href="#">lamaPLC: Energy, power, current, and voltage</a></li> </ul>	2025/05/31 23:32	<a href="#">i2c</a> , <a href="#">i c</a> , <a href="#">communication</a> , <a href="#">arduino</a> , <a href="#">energy</a> , <a href="#">power</a> , <a href="#">current</a> , <a href="#">sensor</a> , <a href="#">ina226</a> , <a href="#">ens160</a> , <a href="#">sciosense</a> , <a href="#">gas-quality</a> , <a href="#">i2c</a> , <a href="#">communication</a> , <a href="#">sensor</a> , <a href="#">arduino</a> , <a href="#">code</a> , <a href="#">eco2</a> , <a href="#">tvoc</a> , <a href="#">aqi</a> , <a href="#">indoor air quality</a> , <a href="#">iaq</a> , <a href="#">co2</a> , <a href="#">voc</a>
<ul style="list-style-type: none"> <li>• <a href="#">LamaPLC: ENS ScioSense Multi-gas sensors with I<sup>2</sup>C communication</a></li> </ul>	2026/04/23 21:52	<a href="#">esp8266</a> , <a href="#">esp32</a> , <a href="#">esp32-c2</a> , <a href="#">esp32-c3</a> , <a href="#">esp32-c5</a> , <a href="#">esp32-c6</a> , <a href="#">esp32-c61</a> , <a href="#">esp32-h2</a> , <a href="#">esp32-s2</a> , <a href="#">esp32-s3</a> , <a href="#">esp32-p4</a> , <a href="#">espressif systems</a> , <a href="#">communication</a> , <a href="#">ethernet</a> , <a href="#">ip</a> , <a href="#">wi-fi</a> , <a href="#">thread</a> , <a href="#">zigbee</a> , <a href="#">matter</a> , <a href="#">homekit</a> , <a href="#">bluetooth</a> , <a href="#">mqtt</a> , <a href="#">adc</a> , <a href="#">spi</a> , <a href="#">uart</a> , <a href="#">i2c</a> , <a href="#">i2s</a> , <a href="#">rmt</a> , <a href="#">pwm</a> , <a href="#">usb</a> , <a href="#">usb otg</a> , <a href="#">twai</a>
<ul style="list-style-type: none"> <li>• <a href="#">lamaPLC: ESP32 / ESP8266</a></li> </ul>	2025/11/22 00:07	<a href="#">gas</a> , <a href="#">sensor</a> , <a href="#">i2c</a> , <a href="#">onewire</a> , <a href="#">communication</a> , <a href="#">mq-3</a> , <a href="#">mq-4</a> , <a href="#">mq-5</a> , <a href="#">mq-6</a> , <a href="#">mq-7</a> , <a href="#">mq-8</a> , <a href="#">mq-9</a> , <a href="#">mq-135</a> , <a href="#">gm-102b</a> , <a href="#">gm-302b</a> , <a href="#">gm-502b</a> , <a href="#">gm-702b</a> , <a href="#">alcohol</a> , <a href="#">ch4</a> , <a href="#">natural gas</a> , <a href="#">smoke</a> , <a href="#">lng</a> , <a href="#">co</a> , <a href="#">co2</a> , <a href="#">lpg</a> , <a href="#">h2</a> , <a href="#">iso-butane</a> , <a href="#">nox</a> , <a href="#">nh3</a> , <a href="#">benzene</a> , <a href="#">town gas</a> , <a href="#">formaldehyde</a> , <a href="#">propane</a> , <a href="#">humidity</a> , <a href="#">temperature</a> , <a href="#">voc</a> , <a href="#">grv gas sens v2</a>
<ul style="list-style-type: none"> <li>• <a href="#">LamaPLC: Gas sensors</a></li> </ul>	2023/07/01 17:29	<a href="#">stmicroelectronics</a> , <a href="#">lsm303dlhc</a> , <a href="#">i2c</a> , <a href="#">lsm303</a> , <a href="#">sensor</a> , <a href="#">gy-511</a> , <a href="#">6dof</a> , <a href="#">pololu</a> , <a href="#">module</a> , <a href="#">arduino</a>
<ul style="list-style-type: none"> <li>• <a href="#">lamaPLC: GY-511 6DOF sensor module</a></li> </ul>	2026/03/22 01:44	<a href="#">ak8963</a> , <a href="#">gy-9250</a> , <a href="#">mpu-9250</a> , <a href="#">9-axis</a> , <a href="#">motion detection</a> , <a href="#">magnetometer</a> , <a href="#">communication</a> , <a href="#">i c</a> , <a href="#">i2c</a> , <a href="#">spi</a>
<ul style="list-style-type: none"> <li>• <a href="#">LamaPLC: GY-9250 MPU-9250/6500 9-axis Attitude Sensor Board</a></li> </ul>	2026/04/23 21:52	<a href="#">sht21</a> , <a href="#">htu21</a> , <a href="#">si7021</a> , <a href="#">gy-21</a> , <a href="#">gy-213v</a> , <a href="#">hdc1080</a> , <a href="#">gy-213v-hdc1080</a> , <a href="#">cjmcu</a> , <a href="#">cjmcu-1080</a> , <a href="#">texas instruments</a> , <a href="#">temperature</a> , <a href="#">humidity</a> , <a href="#">sensor</a> , <a href="#">i2c</a> , <a href="#">communication</a> , <a href="#">arduino</a> , <a href="#">code</a>
<ul style="list-style-type: none"> <li>• <a href="#">LamaPLC: HDC Texas Instruments Temperature/humidity sensors with I<sup>2</sup>C communication</a></li> </ul>	2026/04/23 21:52	

- [lamaPLC: HT16K33 display controller](#) 2026/04/23 21:51 [i2c](#), [7-segment display](#), [display](#), [ht16k33](#), [arduino](#)
- [LamaPLC: HTU TE Connectivity temperature/humidity sensors with I<sup>2</sup>C communication](#) 2026/04/23 21:52 [htu](#), [htu31d](#), [htu21d](#), [htu20d](#), [sht20](#), [htu20](#), [sht21](#), [htu21](#), [si7021](#), [gy-21](#), [gy-213v](#), [hdc1080](#), [si702](#), [gy-20](#), [sht31](#), [htu31](#), [si7031](#), [gy-31](#), [te connectivity](#), [temperature](#), [humidity](#), [i2c](#), [communication](#), [sensor](#), [arduino](#), [code](#)
- [lamaPLC: INA modules with Arduino libraries](#) 2026/04/11 19:54 [i2c](#), [i c](#), [communication](#), [arduino](#), [energy](#), [power](#), [current](#), [monitor](#), [sensor](#), [ina219](#), [gy-219](#), [ina226](#), [gy-216](#), [ina228](#), [gy-228](#), [ina237](#), [ina238](#), [ina260](#), [ina3221](#), [ina](#)
- [lamaPLC: INA226 - current/voltage/power monitor with I<sup>2</sup>C communication](#) 2026/04/23 21:52 [i2c](#), [i c](#), [communication](#), [arduino](#), [energy](#), [power](#), [current](#), [monitor](#), [sensor](#), [ina226](#), [ina219](#), [ina](#)
- [lamaPLC: LCD 1602/2004 with I<sup>2</sup>C communication](#) 2026/02/14 18:27 [communication](#), [i2c](#), [display](#), [lcd](#), [1602](#), [2004](#), [hd44780](#), [pcf8574](#), [pcf8574t](#), [pcf8574at](#), [arduino](#)
- [LamaPLC: MAX30100/MAX30102 Heart Rate Click Sensor Module](#) 2026/04/23 21:52 [max30102](#), [max30100](#), [heart rate click](#), [sensor](#), [communication](#), [i2c](#), [arduino](#), [code](#)
- [lamaPLC: MCP23017 / MCP23S17 16-Bit I/O Expander with Serial Interface I<sup>2</sup>C / SPI](#) 2026/04/23 21:52 [communication](#), [i2c](#), [mcp23017](#), [mcp23s17](#), [spi](#), [i o expander](#), [serial](#), [cjmcu-2317](#), [cjmcu](#)
- [LamaPLC: Pixart PAJ7620U2 Gesture recognition sensors/module with I<sup>2</sup>C communication](#) 2026/04/23 21:52 [paj7620u2](#), [gy-paj7620](#), [pixart](#), [gesture recognition](#), [i2c](#), [communication](#), [sensor](#), [arduino](#), [code](#)
- [LamaPLC: SC16IS750 / SC16IS752: One or two serial \(UART\) ports from microcontroller via I<sup>2</sup>C or SPI communication](#) 2026/04/23 21:52 [cjmcu-750](#), [cjmcu-752](#), [cjmcu](#), [nxp](#), [sc16is750](#), [sc16is752](#), [uart](#), [serial](#), [i2c](#), [spi](#), [modul](#), [converter](#), [arduino](#), [code](#)
- [LamaPLC: SGP Sensirion TVOC/VOC sensors with I<sup>2</sup>C communication](#) 2026/04/15 19:41 [sgp30](#), [sgp40](#), [sgp41](#), [sensirion](#), [gas-sensor](#), [i2c](#), [communication](#), [sensor](#), [arduino](#), [code](#), [eco2](#), [voc](#), [tvoc](#), [indoor air quality](#), [iaq](#), [nox](#), [hydrogen](#)
- [LamaPLC: SHT Sensirion Temperature/humidity sensor with I<sup>2</sup>C communication](#) 2026/04/23 21:52 [sht20](#), [sht21](#), [sht25](#), [sht30](#), [sht31](#), [sht35](#), [sht40](#), [gy21](#), [temperature](#), [humidity](#), [i2c](#), [communication](#), [sensor](#), [arduino](#), [code](#)
- [lamaPLC: Signal level converters](#) 2026/02/14 23:47 [pca9306](#), [i2c](#), [voltage](#), [level](#), [converter](#)
- [lamaPLC: TCA9548A \(HW617\); Low-Voltage 8-Channel I<sup>2</sup>C Switch Module](#) 2026/02/14 23:51 [tca9548a](#), [hw617](#), [i2c](#), [switch](#), [communication](#), [expansion board](#), [arduino](#)
- [lamaPLC: TM1637 7-segment display](#) 2026/02/14 18:26 [i2c](#), [7-segment display](#), [display](#), [tm1637](#), [arduino](#)
- [LamaPLC: TOFnnnC STMicroelectronics Time-of-Flight \(ToF\) sensors with I<sup>2</sup>C communication](#) 2026/04/23 21:52 [tof050c](#), [vl6180](#), [tof200c](#), [vl53l0x](#), [tof400c](#), [vl53l1x](#), [stmicroelectronics](#), [time-of-flight](#), [tof](#), [i2c](#), [communication](#), [sensor](#), [arduino](#), [code](#)

- [LamaPLC: VL53Lnn STMicroelectronics time-of-flight \(ToF\) laser-ranging sensors with I<sup>2</sup>C communication](#) 2026/04/23 21:52 [vl53l0x, vl53l1x, vl53l0 1xv2, gy-530, time-of-flight, tof, laser-ranging, i2c, communication, sensor, arduino, code](#)
- [LamaPLC: VL6180X STMicroelectronics Time-of-Flight \(ToF\) sensor with I<sup>2</sup>C communication](#) 2026/04/23 21:52 [vl6180x, stmicroelectronics, time-of-flight, tof, i2c, communication, sensor, arduino, code](#)
- [Magnetic angle sensors](#) 2026/03/05 21:19 [magnetic angle sensor, magnetic flux, sensor, spi, i2c, pwm, communication, modul, as5047p, as5600, mt6701, mt6816, mt6835, tle5012b, amr, gmr, tmr, anisotropic magnetoresistive](#)
- [SSH1106/SSD1306 OLED Display with I<sup>2</sup>C communication](#) 2026/02/14 18:27 [i2c, oled, display, ssd1306, sh1106, ssh1106, arduino, cmos](#)

[DHT11](#), [DHT20](#), [DHT22](#), [temperature](#), [humidity](#), [pressure](#), [sensor](#), [1-wire](#), [arduino](#), [code](#)

This page has been accessed for: Today: 2, Until now: 4

From:  
<https://www.lamaplc.de/> - **lamaPLC**

Permanent link:  
<https://www.lamaplc.de/doku.php?id=sensor:dht>

Last update: **2026/04/21 20:47**

