


LamaPLC: Allegro ACS758 Hall-effect linear current sensors

The provided part numbers refer to specific models within the **Allegro ACS758 series** of Hall-effect linear current sensor integrated circuits (ICs), which primarily differ in their current-sensing range, sensitivity, and operating temperature range.



Part Number	Current Range	Sensitivity (Typ.)	Operating Temp. Range
ACS758LCB-050B (CJMCU-758)	±50 Amps	40 mV/A	-40 to 150 °C
ACS758LCB-100B	±100 Amps	20 mV/A	-40 to 150 °C
ACS758KCB-150B	±150 Amps	13.3 mV/A	-40 to 125 °C
ACS758ECB-200B	±200 Amps	10 mV/A	-40 to 85 °C

- **Supply Voltage:** 3.0 to 5.5 V.
- **Internal Conductor Resistance:** Ultra-low 100 $\mu\Omega$, providing minimal power loss.
- **Bandwidth:** Typically 120 kHz.
- **Zero Current Output:** For these bidirectional (“B”) models with a 5V VCC, the output voltage is typically VCC/2 (2.5V) when no current is flowing.

CJMCU-758 Pinout

Low power



- **VCC:** Power supply input (3.0V to 5.5V).
- **GND:** Ground connection.
- **OU1:** Direct analog signal from the sensor.
- **OU2:** Buffered signal through an onboard op-amp (often a Texas Instruments LM358 or similar) to reduce noise and drive longer cables.

Power path

- **IP+:** Current input.
- **IP-:** Current output.

Directionality: For bidirectional (“B”) models, current can flow in either direction. For unidirectional

("U") models, current must flow from IP+ to IP- for a positive voltage increase.



If you'd like to support the development of the site with the price of a coffee — or a few — [please do so here](#).

Here's a handy tip: you can quickly save this page as a PDF by clicking "export to PDF" in the menu on the right side of the screen.

2026/02/14 23:38

Arduino code

This code reads a bidirectional sensor (such as the models you listed) and computes the DC current. It assumes a 5V Arduino and that the sensor is powered by 5V.

Select the *mVperAmp* value based on your specific ACS758 model:

- 050B: 40 mV/A
- 100B: 20 mV/A
- 150B: 13.3 mV/A
- 200B: 10 mV/A

```
const int sensorPin = A0;           // Pin connected to CJMCU-758 OUT
int mVperAmp = 40;                  // Change to 20, 13.3, or 10 based on model
int ACSoffset = 2500;              // 2.5V (VCC/2) is the 0A midpoint for
bidirectional sensors

void setup() {
  Serial.begin(9600);
}

void loop() {
  // 1. Read raw ADC value (0-1023)
  int rawValue = analogRead(sensorPin);

  // 2. Convert raw value to voltage in mV
  // 5000mV / 1024 ADC steps = 4.88mV per step
  double voltage = (rawValue / 1023.0) * 5000;

  // 3. Subtract offset and divide by sensitivity to get Amps
  double current = (voltage - ACSoffset) / mVperAmp;

  Serial.print("Raw: "); Serial.print(rawValue);
  Serial.print(" | Voltage(mV): "); Serial.print(voltage);
  Serial.print(" | Current(A): "); Serial.println(current, 2);

  delay(500);
}
```

}

Key Considerations

- **Calibration:** The quiescent offset (voltage at 0 Amps) is theoretically 2500 mV but often varies slightly due to power supply noise or stray magnetic fields. Measure the voltage at 0 A, and update the ACSoffset in your code for improved accuracy.
- **3.3V Microcontrollers:** If using an ESP32 or Arduino Due, you must use a voltage divider on the output to drop it below 3.3V, or use a 3.3V reference in your calculations (the sensitivity will also be lower).
- **Averaging:** To reduce jitter, take 10-100 samples in your loop and compute the mean.

CJMCU topics on lamaPLC

Page	Date	Tags
• LamaPLC: Allegro ACS758 Hall-effect linear current sensors	2026/04/23 21:52	cjmcu , cjmcu-758 , acs758 , acs758lcb-050b , acs758lcb-100b , acs758kcb-150b , acs758ecb-200b , hall-effect , current , sensor , analog , arduino , code
• LamaPLC: BMP/BME Bosch Temperature/Humidity/Pressure sensors with I²C communication	2026/04/23 21:52	bme280 , bme680 , bmp180 , bmp280 , hw-611 , hw611 , bosch , temperature , humidity , pressure , sensor , arduino , i2c , communication , cjmcu
• lamaPLC: CJMCU-164; SN74HC164D 8-bit Shift Register Module	2026/03/06 01:19	cjmcu-164 , sn74hc164d , 8-bit shift register , communication , 7-segment , cjmcu , arduino
• LamaPLC: CJMCU-219/INA-219 breakout board/IC with I²C communication	2026/04/23 21:52	cjmcu-219 , ina-219 , ina219 , breakout board , i2c , communication , sensor , voltage , current , arduino , code , cjmcu
• LamaPLC: CJMCU-3216 / AP-3216 integrated digital ambient light and proximity sensor module/IC with I²C communication	2026/04/23 21:52	cjmcu-3216 , cjmcu , ap-3216 , ap3216 , ambient light , proximity , sensor , arduino , code , i2c , communication
• LamaPLC: CJMCU-3901/PMW-3901 compact optical flow sensor module/IC by PixArt with SPI communication	2026/04/23 21:52	cjmcu-3901 , cjmcu , pmw3901 , pmw-3901 , optical flow , sensor , pixart , spi , communication , arduino , code , pmw3901mb-txqt
• LamaPLC: CJMCU-6701: Biosensor for measuring Galvanic Skin Response (GSR) with SPI communication	2026/04/23 21:52	cjmcu , cjmcu-6701 , acs758 , acs-758 , galvanic skin response , gsr , electrodermal activity , eda , spi , communication , arduino , code , sensor , healthcare
• LamaPLC: CJMCU-6814 combined gas sensor module for CO, NO₂, NH₃	2026/04/23 21:52	analog , cjmcu , cjmcu-6814 , mics6814 , mics-6814 , sensor , arduino , code , carbon monoxide , co , ammonia , nh₃ , nitrogen dioxide , no₂
• LamaPLC: CJMCU-8221 Analog Devices Precision instrumentation amplifier module	2026/04/23 21:52	cjmcu-8221 , ad8221ar , analog devices , amplifier , sensor , cjmcu

- [LamaPLC: HDC Texas Instruments Temperature/humidity sensors with I²C communication](#) 2026/04/23 21:52 [sht21, htu21, si7021, gy-21, gy-213v, hdc1080, gy-213v-hdc1080, cjmcu, cjmcu-1080, texas instruments, temperature, humidity, sensor, i2c, communication, arduino, code](#)
- [lamaPLC: MCP23017 / MCP23S17 16-Bit I/O Expander with Serial Interface I²C / SPI](#) 2026/04/23 21:52 [communication, i2c, mcp23017, mcp23s17, spi, i o expander, serial, cjmcu-2317, cjmcu](#)
- [LamaPLC: SC16IS750 / SC16IS752: One or two serial \(UART\) ports from microcontroller via I²C or SPI communication](#) 2026/04/23 21:52 [cjmcu-750, cjmcu-752, cjmcu, nxp, sc16is750, sc16is752, uart, serial, i2c, spi, modul, converter, arduino, code](#)

[CJMCU](#), [CJMCU-758](#), [ACS758](#), [ACS758LCB-050B](#), [ACS758LCB-100B](#), [ACS758KCB-150B](#), [ACS758ECB-200B](#), [Hall-effect](#), [current](#), [sensor](#), [analog](#), [arduino](#), [code](#)

This page has been accessed for: Today: 2, Until now: 4

From:
<https://www.lamaplc.de/> - **lamaPLC**

Permanent link:
<https://www.lamaplc.de/doku.php?id=sensor:acs758>

Last update: **2026/04/21 20:47**

