

LamaPLC: MH-Z19 series of NDIR CO₂ sensors

The MH-Z19 sensor is manufactured by **Winsen Ltd.**, China, and uses the *non-dispersive infrared (NDIR)* principle to detect the presence of CO₂ in the air.



The **MH-Z19** series of NDIR CO₂ sensors shares core technology but differs in operational parameters, including power consumption, sampling rate, and calibration cycles.

The **MH-Z19C** is generally considered the successor to the MH-Z19B, offering improved consistency and lower power usage.

Feature	MH-Z19	MH-Z19B	MH-Z19C	MH-Z19D	MH-Z19E
Working Voltage	3.6~5.5V DC	4.5~5.5V DC	5.0±0.1V DC	5.0±0.1V DC	4.5V~5.5V DC
Average Current	< 18mA	< 60mA (@5V)	< 40mA (@5V)	< 40mA (@5V)	< 85mA
Detection Range	0-2000/5000 ppm	0-5000/10000 ppm	400-5000 ppm	400-5000 ppm	0-5000 ppm
Accuracy	±(50ppm+5% reading)	±(50ppm+3% reading)	±(50ppm+5% reading)	Not specified in general specs	
Response Time (T90)	< 60s	< 120s	< 120s	< 120s	< 90s
Preheat Time	3 min	3 min	1 min	1 min	3 min
Sampling Period	N/A	5 seconds	1 second	1 second	N/A
Analog Output / Communication	Analog 0.4-2V	Analog 0.4-2V	Analog, UART/PWM only on some board	Analog, UART/PWM only on some board	Analog 0.4-2V

Key Differences and Features

- **MH-Z19B vs. MH-Z19C:** The primary practical difference is the C version's faster sampling rate (1s vs. 5s) and lower power consumption, making it more responsive and efficient. The B version has two CO₂ gas-receiving windows, while the C version has one.
- **MH-Z19E:** This model is described as mid- to low-end, likely a cost-optimized variant with slightly different specifications, though comprehensive direct comparison data are less common than for the B and C models.
- **Common Features:** All models use the same NDIR (Non-Dispersive Infrared) principle, feature a gold-plated gas chamber for stability and long life, and include built-in temperature compensation.
- **Output Modes:** All listed variants support both UART (TTL-level, 3.3V) and PWM output modes, enabling flexible integration with microcontrollers such as Arduino or Raspberry Pi.



If you'd like to support the development of the site with the price of a coffee — or a few — [please do so here](#).

Here's a handy tip: you can quickly save this page as a PDF by clicking "export to PDF" in the menu on the right side of the screen.

2026/02/14 23:38

The **MH-Z19** units can be integrated into the **Tasmota** system. More details are available here: <https://tasmota.github.io/docs/MH-Z19B/>

Arduino and MH-Z19C, UART vs. Analog Output

Feature	UART (Digital)	Analog (Voltage)
Data Format	Digital packet (exact PPM number)	Voltage (0.4V to 2.0V)
Precision	High: No signal loss or interference	Lower: Susceptible to "noise" and voltage drops
Calibration	Accessible via software commands	Requires manual hardware grounding (HD pin)
Extra Data	Provides Temperature and Error Codes	CO ₂ levels only
Wiring	4 wires (VCC, GND, TX, RX)	3 wires (VCC, GND, Vout)
Processing	Requires a library or serial parsing	Requires analogRead() and math mapping

Why is UART usually better

- **Noise Immunity:** Analog signals can fluctuate if your power supply is unstable or your wires are long. UART transmits bits, so the number 800 ppm always arrives as 800 ppm in the Winsen MH-Z19C Datasheet.
- **Resolution:** The Arduino's `analogRead()` splits the 0-5V range into 1024 steps. Since the sensor only uses the 0.4V-2.0V range, you only get about 320 steps of resolution to represent 5000ppm. UART provides full 1 ppm resolution.
- **Advanced Features:** Through UART commands, you can change the detection range (e.g., 2000ppm vs 5000ppm) or toggle *Auto-Baseline Calibration* (**ABC**).

See:

- 1: Arduino and MH-Z19C, utilize the Analog input
- 2: Arduino and MH-Z19C, utilize the UART communication

1: Arduino and MH-Z19C, utilize the Analog input

To read the **MH-Z19C** sensor's analog output with an Arduino, utilize its built-in ADC to measure the voltage from its analog pin. The sensor produces a voltage from 0.4V at 0 ppm up to 2.0V at 5000 ppm, which is scaled to the Arduino's analog input range of 0 to 1023.

Wiring Diagram

Connect the MH-Z19C to the Arduino as follows:

- VCC pin to the 5V pin on the Arduino.
- GND pin to a GND pin on the Arduino.

- Analog Out pin to an analog input pin, such as A0.

Do not use the HD pin unless you intend to perform manual zero-point calibration (by connecting it to GND for 7 seconds in 400ppm air).

This code reads the analog voltage and converts it to ppm values within the standard 0-5000 ppm range, using a 0.4V-2.0V output:

```
/*
 * MH-Z19C Analog Reading Example
 * Reads the 0.4V-2.0V analog output and converts it to ppm.
 */

const int CO2_ANALOG_PIN = A0; // Connect the MH-Z19C Analog Out pin to A0
const int MIN_VOLTAGE_ADC = 82; // Approx. ADC value for 0.4V (0.4V / 5V * 1023)
const int MAX_VOLTAGE_ADC = 410; // Approx. ADC value for 2.0V (2.0V / 5V * 1023)
const int MIN_PPM = 0; // Corresponds to 0.4V
const int MAX_PPM = 5000; // Corresponds to 2.0V

void setup() {
  Serial.begin(9600);
  Serial.println("MH-Z19C Analog Reader Starting...");
  pinMode(CO2_ANALOG_PIN, INPUT);
}

void loop() {
  // Read the raw analog value (0-1023 range for 5V Arduino)
  int rawADCValue = analogRead(CO2_ANALOG_PIN);

  // Convert the raw ADC value to CO2 ppm using the map function
  long co2_ppm = map(rawADCValue, MIN_VOLTAGE_ADC, MAX_VOLTAGE_ADC, MIN_PPM,
MAX_PPM);

  // Print the results to the Serial Monitor
  Serial.print("Raw ADC Value: ");
  Serial.print(rawADCValue);
  Serial.print(" | Estimated CO2 (ppm): ");
  // Constrain the value to the sensor's valid range
  if (co2_ppm < MIN_PPM) co2_ppm = MIN_PPM;
  if (co2_ppm > MAX_PPM) co2_ppm = MAX_PPM;
  Serial.println(co2_ppm);

  delay(2000); // Read every 2 seconds
}
```

Important Notes

- **Accuracy:** According to experts at Wolles Elektronikiste, the analog method may exhibit “significant deviations” compared with UART (serial) communication. For better precision, the

serial interface is highly recommended.

- **Voltage Divider:** If your Arduino runs at 3.3V, you may need to adjust the `MIN_VOLTAGE_ADC` and `MAX_VOLTAGE_ADC` values based on a 3.3V reference (e.g., using `analogReference(EXTERNAL)` with a precise 2.5V source or using the internal 1.1V reference, though this requires a voltage divider because the output goes up to 2V).
- **Warm-up:** The sensor requires a 3-minute warm-up after power-on to ensure accurate readings.

2: Arduino and MH-Z19C, utilize the UART communication

To get the most accurate readings from the MH-Z19C, using the UART (Serial) interface is the gold standard. It allows you to read digital values directly, avoiding the voltage fluctuations of analog pins.

Wiring (UART)

Connect the sensor to your Arduino (e.g., Uno) using SoftwareSerial to keep the main USB port free for debugging:

- **VCC:** 5V
- **GND:** GND
- **TX (Sensor):** Pin 10 (Arduino RX)
- **RX (Sensor):** Pin 11 (Arduino TX)

Recommended Library

For a reliable setup, use the **MH-Z19 Library** by Jonathan T. available in the Arduino Library Manager.

```
#include <SoftwareSerial.h>
#include <MHZ19.h>

#define RX_PIN 10 // Sensor TX ->
Arduino 10
#define TX_PIN 11 // Sensor RX ->
Arduino 11
#define BAUDRATE 9600

MHZ19 myMHZ19;
SoftwareSerial mySerial(RX_PIN, TX_PIN);

void setup() {
  Serial.begin(9600); // Device to PC
  mySerial.begin(BAUDRATE); // Device to
  Sensor
  myMHZ19.begin(mySerial); // Initialize
  library

  myMHZ19.autoCalibration(true); // Turn on Auto
  Calibration (ABC)
  Serial.println("Sensor warming up (3 mins recommended)...");
```

```

}

void loop() {
  int co2 = myMHZ19.getC02(); // Request CO2 ppm

  if (myMHZ19.errorCode == RESULT_OK) {
    Serial.print("CO2 (ppm): ");
    Serial.println(co2);

    int temp = myMHZ19.getTemperature(); // Request
    Temperature
    Serial.print("Temperature (C): ");
    Serial.println(temp);
  } else {
    Serial.print("Error Code: ");
    Serial.println(myMHZ19.errorCode);
  }

  delay(5000); // Sensor
  refreshes every few seconds
}

```

Pro Tips for MH-Z19C

- **Logic Levels:** The MH-Z19C uses 3.3V logic for TX/RX. While many Arduinos (like the Uno) can handle this, using a Logic-Level Converter is safer for long-term use.
- **Warm-up:** The Official Datasheet from Winsen specifies a 1-minute preheat for the “C” model before readings stabilize.
- **ABC Logic:** The *Auto-Baseline Calibration (ABC)* assumes the sensor sees “fresh air” (400ppm) at least once every 24 hours. If you are using this in a sealed lab, turn ABC off.

Sensor topics on lamaPLC

Page	Date	Tags
• lamaPLC project: Arduino - OLED SH1106 with AHT20/BMP280 Sensor	2026/04/23 21:51	bmp280 , aht20 , temperature , humidity , pressure , sensor , arduino , oled , sh1106 , arduino code
• lamaPLC project: Arduino - Vibration sensors	2026/04/15 17:21	vibration , sensor , piezoelectric , mems , eddy-current , electrodynamic , gxfm0459 , ldtm-028k , arduino , arduino code
• lamaPLC project: Digitales Potentiometer Board Moduls	2026/04/11 18:29	sensor , module , arduino code , renesas , x9c series , x9c102 , x9c103 , x9c104 , x9c503 , xdcp , digitally controlled potentiometer
• lamaPLC project: Sension SCD CO² measurement module	2026/04/15 19:34	bmp280 , aht20 , temperature , humidity , pressure , sensor , arduino , oled , sh1106 , arduino code

• lamaPLC: A0221AU / A02YYUW Waterproof Ultrasonic Distance Sensor with UART communication	2026/04/23 21:52	a0221au , a02yyuw , waterproof , ultrasonic , distance , sensor , uart , ip67 , serial , sen0311 , dfrobot
• LamaPLC: AHT10 Modul	2026/03/22 03:14	communication , i2c , temperature , humidity , sensor , aht , aht 10 , modul
• LamaPLC: AHT20 / BMP280 Modul	2026/04/23 21:52	bmp280 , aht20 , adafruit , temperature , humidity , pressure , sensor , arduino , code , i2c
• LamaPLC: Allegro ACS758 Hall-effect linear current sensors	2026/04/23 21:52	cjmcu , cjmcu-758 , acs758 , acs758lcb-050b , acs758lcb-100b , acs758kcb-150b , acs758ecb-200b , hall-effect , current , sensor , analog , arduino , code
• LamaPLC: APDS - Avago ALS and proximity detection sensors with I²C communication	2026/04/23 21:52	avago , apds-9900 , apds-9930 , apds-9960 , als , proximity , detection , gesture recognition , gesture , i2c , communication , sensor , arduino , code
• lamaPLC: AS5600 Magnetic Induction Angle Measurement Sensor Module	2026/03/28 23:50	communication , i2c , as5600 , as-5600 , magnetic , induction , angle , sensor
• LamaPLC: BMP/BME Bosch Temperature/Humidity/Pressure sensors with I²C communication	2026/04/23 21:52	bme280 , bme680 , bmp180 , bmp280 , hw-611 , hw611 , bosch , temperature , humidity , pressure , sensor , arduino , i2c , communication , cjmcu
• LamaPLC: BQ25570 / CJMCU-2557 - Texas Instruments nano-power management IC and module	2026/04/23 21:52	bq25570 , sensor , texas instruments , nano-power management , dc-dc boost charger , mppt , solar , thermoelectric , piezoelectric
• LamaPLC: CJMCU-219/INA-219 breakout board/IC with I²C communication	2026/04/23 21:52	cjmcu-219 , ina-219 , ina219 , breakout board , i2c , communication , sensor , voltage , current , arduino , code , cjmcu
• LamaPLC: CJMCU-3216 / AP-3216 integrated digital ambient light and proximity sensor module/IC with I²C communication	2026/04/23 21:52	cjmcu-3216 , cjmcu , ap-3216 , ap3216 , ambient light , proximity , sensor , arduino , code , i2c , communication
• LamaPLC: CJMCU-3901/PMW-3901 compact optical flow sensor module/IC by PixArt with SPI communication	2026/04/23 21:52	cjmcu-3901 , cjmcu , pmw3901 , pmw-3901 , optical flow , sensor , pixart , spi , communication , arduino , code , pmw3901mb-txqt
• LamaPLC: CJMCU-6701: Biosensor for measuring Galvanic Skin Response (GSR) with SPI communication	2026/04/23 21:52	cjmcu , cjmcu-6701 , acs758 , acs-758 , galvanic skin response , gsr , electrodermal activity , eda , spi , communication , arduino , code , sensor , healthcare
• LamaPLC: CJMCU-6814 combined gas sensor module for CO, NO₂, NH₃	2026/04/23 21:52	analog , cjmcu , cjmcu-6814 , mics6814 , mics-6814 , sensor , arduino , code , carbon monoxide , co , ammonia , nh₃ , nitrogen dioxide , no₂
• lamaPLC: CJMCU-811 CCS811 Gas Sensor (VOCs TVOC CO₂)	2026/03/22 00:08	cjmcu-811 , ccs811 , gas , sensor , vocs , tvoc , eco2 , co2 , arduino , air quality , metal oxide , mox , i2c
• LamaPLC: CJMCU-8221 Analog Devices Precision instrumentation amplifier module	2026/04/23 21:52	cjmcu-8221 , ad8221ar , analog devices , amplifier , sensor , cjmcu

• LamaPLC: D6T Omron Non-Contact Thermal Sensors with I ² C communication	2026/04/23 21:52	d6t, d6t-32l, d6t-44l, d6t-8l, d6t-1a, omron, non-contact, thermal, sensor, i2c, arduino, code
• LamaPLC: DHT Temperature /Humidity sensors with 1-wire / I ² C communication	2026/04/23 21:52	dht11, dht20, dht22, temperature, humidity, pressure, sensor, 1-wire, arduino, code
• LamaPLC: DPS Infineon Temperature/Pressure sensors with I2C communication	2026/04/23 21:52	dps310, infineon, temperature, pressure, sensor, arduino, i2c, communication, code
• lamaPLC: DS18B20 1-Wire Digital Thermometer	2026/04/23 21:52	ds18b20, sensor, 1-wire, communication, arduino, thermometer, parasitic mode
• lamaPLC: Energy, power, current, and voltage	2025/05/31 23:32	i2c, i c, communication, arduino, energy, power, current, sensor, ina226
• LamaPLC: ENS ScioSense Multi-gas sensors with I ² C communication	2026/04/23 21:52	ens160, sciosense, gas-quality, i2c, communication, sensor, arduino, code, eco ₂ , tvoc, aqi, indoor air quality, iaq, co ₂ , voc
• lamaPLC: ENS160 + AHT21 Air Quality Sensor - CO, ECO, TVOC, Temp & Humidity Module	2026/04/23 21:52	arduino, ens160, aht21, air quality, sensor, co, eco, tvoc, module, aqi
• LamaPLC: Gas sensors	2023/07/01 17:29	gas, sensor, i2c, onewire, communication, mq-3, mq-4, mq-5, mq-6, mq-7, mq-8, mq-9, mq-135, gm-102b, gm-302b, gm-502b, gm-702b, alcohol, ch ₄ , natural gas, smoke, lng, co, co ₂ , lpg, h ₂ , iso-butane, nox, nh ₃ , benzene, town gas, formaldehyde, propane, humidity, temperature, voc, grv gas sens v2
• LamaPLC: GM MEMS Gas-sensors	2026/04/23 21:52	gm-102b, gm-302b, gm-502b, gm-702b, mems, gas-quality, sensor, arduino, code, nitrogen dioxide, no ₂ , volatile organic compounds, voc, carbon monoxide, co, ethyl alcohol, c ₂ h ₅ ch, formaldehyde, ch ₂ o, alcohol, c ₂ h ₅ oh
• lamaPLC: GY-511 6DOF sensor module	2026/03/22 01:44	stmicroelectronics, lsm303dlhc, i2c, lsm303, sensor, gy-511, 6dof, pololu, module, arduino
• LamaPLC: HC-SR04 Ultrasonic Sensor Module	2026/04/23 21:52	hc-sr04, ultrasonic, sensor, arduino, code
• LamaPLC: HDC Texas Instruments Temperature/humidity sensors with I ² C communication	2026/04/23 21:52	sht21, htu21, si7021, gy-21, gy-213v, hdc1080, gy-213v-hdc1080, cjmcu, cjmcu-1080, texas instruments, temperature, humidity, sensor, i2c, communication, arduino, code
• LamaPLC: HTU TE Connectivity temperature/humidity sensors with I ² C communication	2026/04/23 21:52	htu, htu31d, htu21d, htu20d, sht20, htu20, sht21, htu21, si7021, gy-21, gy-213v, hdc1080, si702, gy-20, sht31, htu31, si7031, gy-31, te connectivity, temperature, humidity, i2c, communication, sensor, arduino, code

• LamaPLC: HX711 24-bit analog-to-digital converter (ADC)	2026/04/11 18:28	hx711, hx-711, analog-to-digital, adc, converter, load cell, wheatstone bridge, weight, sensor, communication, arduino, code
• lamaPLC: INA modules with Arduino libraries	2026/04/11 19:54	i2c, i c, communication, arduino, energy, power, current, monitor, sensor, ina219, gy-219, ina226, gy-216, ina228, gy-228, ina237, ina238, ina260, ina3221, ina
• lamaPLC: INA226 - current/voltage/power monitor with I²C communication	2026/04/23 21:52	i2c, i c, communication, arduino, energy, power, current, monitor, sensor, ina226, ina219, ina
• lamaPLC: LTC3588 - Nanopower energy harvesting power supply IC	2026/04/23 21:52	communication, arduino, sensor, energy harvesting, energy, ambient power
• LamaPLC: M01 - V0.4 Laser ranging sensor with UART communication	2026/04/23 21:52	distance measurement, laser, distance, sensor, m01
• LamaPLC: MAX30100/MAX30102 Heart Rate Click Sensor Module	2026/04/23 21:52	max30102, max30100, heart rate click, sensor, communication, i2c, arduino, code
• lamaPLC: Max31865 RTD to Digital Converter - PT100/PT1000 Platine	2026/04/23 21:52	max31865, rtd, pt 100, pt 1000, temperature, spi, platinum, arduino, code, sensor, adafruit
• LamaPLC: MAX4466/MAX9814: Low-noise Microphone Preamplifiers	2026/04/23 21:52	audio, microphone, analogue audio, max4466, max9814, max 4466, max 9814, agc, preamplifiers, sensor, arduino, code
• LamaPLC: MH-Z19 series of NDIR CO₂ sensors	2026/04/23 21:52	mh-z19, mh-z19d, mh-z19c, mh-z19b, mh-z19e, ndir, co ₂ , sensor, winsen, uart, pwm, communication, non-dispersive infrared, infrared, ir, temperature, arduino, code, tasmota
• lamaPLC: MPU-6050 (HW-123, GY-521) 6-axis MotionTracking device	2026/03/22 03:13	mpu-6050, hw-123, gy-521, 6-axis motiontracking, dmp, temperature, sensor, mems, arduino code, arduino, accelerometer, gyroscope, tilt
• LamaPLC: MQ Winsen Gas-sensors	2026/04/23 21:52	mq, mq-2, mq-3, mq-4, mq-5, mq-6, mq-7, mq-8, mq-9, mq-131, mq-135, mq-137, winsen, gas-sensor, sensor, arduino, code, alcohol, c ₂ h ₅ oh, benzine gas, smoke, lpg, propane, c ₃ h ₈ , hydrogen, h ₂ , methane, ch ₄ , iso-butane, town gas, ammonia, nh ₃
• LamaPLC: PIR sensors	2026/04/23 21:52	hc-sr501, hc-sr505, am-312, ekmb ekmc, pir, motion, sensor, arduino, code
• LamaPLC: Pixart PAJ7620U2 Gesture recognition sensors/module with I²C communication	2026/04/23 21:52	paj7620u2, gy-paj7620, pixart, gesture recognition, i2c, communication, sensor, arduino, code
• lamaPLC: PT100 / PT1000	2025/09/23 18:59	pt100, pt1000, temperature, sensor, platine, rtd
• lamaPLC: PTA8C04 4-channel PT100 Modbus Modul	2026/02/14 18:42	pta8c04, sensor, modbus, rtu, rs-485, communication, platine, um72

• LamaPLC: RCWL - Microwave radar sensor	2026/04/23 21:52	rcwl-0516, rcwl, microwave, radar, sensor, arduino, code
• lamaPLC: RD-xx - Ai-Thinker Radar Module with UART communication	2026/04/23 21:52	radar, s3km1110, fmcw, rd-01, rd-03, rd-03d, ai-thinker, k-band, 24 ghz, sensor, distance, micro-movements
• LamaPLC: SGP Sensirion TVOC/VOC sensors with I ² C communication	2026/04/15 19:41	sgp30, sgp40, sgp41, sensirion, gas-sensor, i2c, communication, sensor, arduino, code, eco2, voc, tvoc, indoor air quality, iaq, nox, hydrogen
• LamaPLC: SHT Sensirion Temperature/humidity sensor with I ² C communication	2026/04/23 21:52	sht20, sht21, sht25, sht30, sht31, sht35, sht40, gy21, temperature, humidity, i2c, communication, sensor, arduino, code
• LamaPLC: Texas Instruments ADCs: Delta-sigma multi-channel Analog Converters with SPI communication	2026/04/23 21:52	ads111x, ads12xx, delta-sigma, converter, texas instruments, adc, spi, communication, sensor, arduino, code, ads1110, ads1112, ads1113, ads1114, ads1115, ads1118, ads1119, ads1220, ads1232, ads1234, ads1256, ads1261, ads1263, multi channel
• LamaPLC: TOFnnnC STMicroelectronics Time-of-Flight (ToF) sensors with I ² C communication	2026/04/23 21:52	tof050c, vl6180, tof200c, vl53l0x, tof400c, vl53l1x, stmicroelectronics, time-of-flight, tof, i2c, communication, sensor, arduino, code
• LamaPLC: UICPAL Temp.humi.sensor	2023/06/25 00:43	simatic, s7, modbus, communication, temperature, humidity, sensor
• LamaPLC: VL53Lnn STMicroelectronics time-of-flight (ToF) laser-ranging sensors with I ² C communication	2026/04/23 21:52	vl53l0x, vl53l1x, vl53l0 1xv2, gy-530, time-of-flight, tof, laser-ranging, i2c, communication, sensor, arduino, code
• LamaPLC: VL6180X STMicroelectronics Time-of-Flight (ToF) sensor with I ² C communication	2026/04/23 21:52	vl6180x, stmicroelectronics, time-of-flight, tof, i2c, communication, sensor, arduino, code
• LamaPLC: Waveshare TOF Laser Range Sensor with UART / I ² C communication	2026/04/23 21:52	distance measurement, laser, range, sensor, tof, waveshare
• lamaPLC: YR-3180 - Weight sensor module with UART or Modbus communication	2026/02/15 00:00	communication, modbus, rtu, sensor, weight, yr-3180, hx710b, arduino, ttl, rs-485
• Magnetic angle sensors	2026/03/05 21:19	magnetic angle sensor, magnetic flux, sensor, spi, i2c, pwm, communication, modul, as5047p, as5600, mt6701, mt6816, mt6835, tle5012b, amr, gmr, tmr, anisotropic magnetoresistive
• NT18B07: 7 Kanal RS485 Temperatur Sensor with Modbus RTU	2026/02/14 18:49	nt18b07, sensor, modbus, rtu, rs-485, communication, platine
• PT100 / PT1000 sensors	2026/04/23 21:52	rtd, pt100, pt1000, sensor, temperature
• Radar Module RD-xx	2026/04/23 21:52	radar, s3km1110, fmcw, rd-03, k-band, 24 ghz, sensor, distance, micro-movements

MH-Z19, MH-Z19D, MH-Z19C, MH-Z19B, MH-Z19E, NDIR, CO₂, sensor, Winsen, UART, PWM,

[communication](#), [NDIR](#), [Non-Dispersive Infrared](#), [Infrared](#), [IR](#), [temperature](#), [arduino](#), [code](#), [Tasmota](#)

This page has been accessed for: Today: 4, Until now: 5

From:

<https://www.lamaplc.de/> - **lamaPLC**

Permanent link:

https://www.lamaplc.de/doku.php?id=sensor:mh_z19

Last update: **2026/04/21 20:47**

